



LIGHTING & ACCESSORIES

ACTIVE & NEUTRAL LINKS



Data Specification **2023**



AUSTRALIA WIDE DELIVERY
Expedited delivery to all states in Australia



SAME DAY DISPATCH
Orders prior to 12PM will be dispatched the same day



5 YEAR WARRANTY
You can get a trusted 5 Year In House Warranty with CSG

[DESCRIPTION]

Connected Switchgears' active and neutral links are manufactured from a high percentage of brass material. Rated at 500V AC in both 110amp and 350amp. Terminal diameter accepts cable size up to 150mm² with up to 14 terminal holes. All links come with a cover indicating amperage and cable size to comply with Australian Wiring Rules.

[FEATURES]

- Available in Red or Black
- 350amp Links Complete with Allen Key

[TECHNICAL PARAMETERS]

- Rated Voltage: 500V AC

[COMPLIANCE]

- AS/NZS 60947.7.3:2015

[IMAGES]



LA13-350

LN12



LNRCD

[SPECIFICATIONS]

Product Code	Type	Ratings (Amps)	Number of Terminals	Max Cable Sizes	Terminal Sizes
LA5	Active	110A	5	16mm ²	1 x 4mm, 4 x 6mm
LA7	Active	110A	7	16mm ²	4 x 6mm, 3 x 5mm
LA7-350	Active	350A	7	150mm ²	2 x 8mm, 2 x 10mm, 1 x 5mm, 2 x 15mm
LA8	Active	110A	8	25mm ²	8 x 7mm
LA10	Active	110A	10	25mm ²	6 x 5mm, 4 x 7mm
LA12	Active	110A	12	25mm ²	4 x 6mm, 8 x 4mm
LA13-350	Active	350A	13	150mm ²	2 x 4mm, 8 x 5mm, 1 x 8mm, 2 x 15mm
LA14	Active	110A	14	25mm ²	4 x 7mm, 10 x 5mm
LN5	Neutral	110A	5	16mm ²	1 x 4mm, 4 x 6mm
LN7	Neutral	110A	7	16mm ²	4 x 6mm, 3 x 5mm
LN7-350	Neutral	350A	7	150mm ²	2 x 8mm, 2 x 10mm, 1 x 5mm, 2 x 15mm
LN8	Neutral	110A	8	25mm ²	8 x 7mm
LN10	Neutral	110A	10	25mm ²	6 x 5mm, 4 x 7mm
LN12	Neutral	110A	12	25mm ²	4 x 6mm, 8 x 4mm
LN13-350	Neutral	350A	13	150mm ²	2 x 4mm, 8 x 5mm, 1 x 8mm, 2 x 15mm
LN14	Neutral	110A	14	25mm ²	4 x 7mm, 10 x 5mm
LNRC D	Neutral	32A	3	-	-

[WARRANTY]

Connected Switchgear active and neutral links come with a trusted 5 Year In House Warranty. That means that you have peace of mind knowing that if a fault develops within a five year period, Connected Group Australia will cover the cost of replacing the product and it's installation.*

* See our website for full terms and conditions www.connectedswitchgear.com.au